



access units
MOTION 868 MHz range

Applicable to doors
roller · folding · sliding · swing · sectional
guillotine · fast · glass · revolving · barriers

GOBio^e

868 MHz transmission with
biometric activation for door and/
or wall installation



jcmtechnologies
be a step ahead with technology and imagination

JCM biometric transmitter for door or wall installation, offering the utmost user security, reliability and convenience. With a capacity for 10 fingerprints that can be configured so that the programmed doors open after a simple swipe of your finger over the reader.





Versatility

- Forget about looking for keys, all you need is to pass your finger over the reader to open the door.
- Variety of finishes to blend into any surface.
- 2 user levels, Master and basic.
 Master: user who can configure (learn and delete fingerprints) and use the transmitter
 Basic: user who can only use the transmitter.

Greater security

- New "high security" rolling code system with more keying bits.
- Maximum security thanks to JCM's experience combined with the last generation of Biometric's technology. Only programmed finger prints can use the transmitter.

User-friendly

- Equipment installation requires no wiring.
- Compact size allows for it to be built into an electrics box or into the door itself.


Simplified community installation management

The following is available with the ASSISTANT programming tool:

- Database with all equipment, transmitters and proximity cards/tags provided in each installation.
- Possibility of assigning standby codes. Functional transmitters, cards and tags can be sold without having to visit the installation.
- Stolen or lost transmitters, cards and tags can be replaced by new, functional ones without having to visit the installation.
- Registrations via PIN, 1 4-digit code can be allocated to a receiver and all transmitters/proximity elements must have the same PIN to be programmed in the equipment. 2 PIN codes per transmitter is permitted. Also available with the PROGMAN portable programming tool.
- Possibility of personalising devices with the installer code.
- Configuration of equipment parameters such as forbidding the radio and manual programming of devices.

Flexibility and speed when programming equipment

- The transmitters and proximity equipment are programmed by radio without mechanical contact.
- The transmitter must be registered in the receiver like any other control.

TRANSMITTERS	RECEIVERS
 <p>GOBio^e</p> <ul style="list-style-type: none"> • Biometric transmitter for wall installation, 868 MHz, 4 channels. • Nominal range: 100 m (30 m for built-in version and depending on the installation). • Memory: 10 huellas. • Power supply: 2x1.5Vdc lithium battery AAA-type. • Consumption: 200mA. • Battery lasts for approximately 2,5 years. • Light and acoustic operating indicator for low battery, signal transmission and programming. • IP65 PC Plastic box. • High security rolling code, 19 trillion combinations. • Laser-marked series number. • Operating temperature: -20°C a +55°C. • Size: 93 x 93 x 30 mm. 	<p>Receivers MOTION.</p> <p>BASE WAVE STICK CONNECT ACCESS500 ACCESS1000</p> <p>and control panels with built-in receivers</p>

2 versions (surface-mounted and embedded)



Different colours to order



Activation

It works by swiping a predominate finger for each door. Each fingerprint will enable you to open a different door.

